



FT 25-RLH-PNSL-...

096-00027 08.06.2020-01
www.sensopart.com

GENERAL INFORMATION	
Communication mode IO-Link	COM 2
Min. cycle time	2.3 ms
SIO mode	Supported
Length process data	16 Bit
Vendor ID	347 (0x01 0x5B)
Device ID	6613 / 6657
Data storage	Supported
Specification IO-Link	1.1

PROCESS DATA															
SMART-SENSOR PROFILE															
Byte 0							Byte 1								
7	6	5	4	3	2	1	0	7	6	5	4	3	2	1	0
MSB D7	D6	D5	D4	D3	D2	D1	LSB D0	X	X	X	X	X	Signal quality	Switching output Q ₂	Switching output Q ₁
Signal quality 0 ... 100 %															
Signal quality score - adjustable via index 0xC4															
Switching output 2 - only virtual															
Switching output 1 - corresponds to switching output Q ₁ in SIO-mode															

IDENTIFICATION DATA						
Index dec / hex	Access	Data type	Length	Description	Comment	
16 / 0x10	Read	String	Max. 64 Byte	Vendor name	SensoPart Industriesensork GmbH	
17 / 0x11				Vendor text	www.sensopart.com	
18 / 0x12				Product name	FT 25-RLH-PNSL-...	
19 / 0x32				Product ID	609-11015 609-11016 609-11017 609-11018 609-11019 609-11020 609-11021	
20 / 0x11				Product text	Device specific	
23 / 0x17				Firmware revision	1.0	

SMART SENSOR PROFILE PARAMETER									
Index in dec / hex	Access	Data type	Length	Subindex	Default value	Range	Description	Comment	
12 / 0x0C	Read / write	Uint	16 Bit		0x00 0x00	D0, D1, D3	Lock functions	D0 - parameter write access D1 - data storage lock D3 - local user interface lock	
24 / 0x18	Read / write	StringT	32 characters		**** ... ****		Application text	Free text, e.g. item designation	
58 / 0x3A	Read / write	Uint	8 Bit		0	0, 1, 2	Teach channel	0 / 1 = switching channel 1 2 = switching channel 2	
59 / 0x3B	Read	Uint	8 Bit				Teach-in status		
Define switching output Q ₁ (physical pin)									
60 / 0x3C	Read / write	Uint	16 Bit	1	1500	120 ... 1500	Switching point 1	Needed for single, window and two-point mode, in 1/8 mm (e.g. 10 mm = 100 1/8 mm)	
				2	1500	120 ... 1500	Switching point 2	Needed for window and two-point mode, in 1/8 mm (e.g. 10 mm = 100 1/8 mm)	
Set-Up switching output Q ₁ (physical pin)									
61 / 0x3D	Read / write	Uint	8 Bit	1	0	0, 1	NO / NC	0 = NO, 1 = NC	
				2	1	0, 1, 2, 3	Switching mode	0 - disable 1 - single-point mode 2 - window mode ¹⁾ 3 - two-point mode ¹⁾	
				3	0	0	Hysteresis	Not adjustable	
Define switching output Q ₂ (only virtual via IO-Link)									
62 / 0x3E	Read / write	Uint	16 Bit	1	1500	120 ... 1500	Switching point 1	Needed for single, window and two-point mode, in 1/8 mm (e.g. 10 mm = 100 1/8 mm)	
				2	1500	120 ... 1500	Switching point 2	Needed for window and two-point mode, in 1/8 mm (e.g. 10 mm = 100 1/8 mm)	
Set-Up switching output Q ₂ (only virtual via IO-Link)									
63 / 0x3F	Read / write	Uint	8 Bit	1	0	0, 1	NO / NC	0 = NO, 1 = NC	
				2	0	0, 1, 2, 3	Switching mode	0 - disable 1 - single-point mode 2 - window mode ¹⁾ 3 - two-point mode ¹⁾	
				3	0	0	Hysteresis	Not adjustable	

¹⁾ Min. difference between both switchpoints 1 mm

PARAMETER									
Index dec / hex	Access	Data type	Length	Subindex	Default value	Range	Description	Comment	
Read operating data									
88 / 0x58	Read	Uint	32 Bit	1			Counter operating hours	No reset possible	
				2			Counter switch cycle	No reset possible	
Read sensor characteristics									
95 / 0x5F	Read	String		1	12 ... 150 mm		Operating range		
				5	Laser, red, 650 nm, class 1		Type of light and laser class		
				6	≤ 30 mA		No-load current		
				7	≤ 1000 Hz		Switching frequency		
			9	-20 ... 60 °C			Ambient temperature		
Signal quality level									
196 / 0xC4	Read / write	Uint	8 Bit		10	10 ... 90	Signal quality level	If below 10 % no stable detection	
Smart functions Q ₁ (physical pin)									
208 / 0xD0	Read / write	Uint	16 Bit	1	0	0 ... 65535	Counter		
				2	0	0 ... 65535	On delay	In ms, adjustable in 1 ms	
				3	0	0 ... 65535	Off delay	In ms, adjustable in 1 ms	
				4	0	0 ... 65535	Impulse	In ms, adjustable in 1 ms	
				5	0	0 ... 500	Monitoring frequency	In 1/4 Hz, adjustable in 0.1 Hz steps ²⁾	
Smart functions Q ₂ on virtual switching output Q ₂									
209 / 0xD1	Read / write	Uint	16 Bit	1	0	0 ... 65535	Counter		
				2	0	0 ... 65535	On delay	In ms, adjustable in 1 ms	
				3	0	0 ... 65535	Off delay	In ms, adjustable in 1 ms	
				4	0	0 ... 65535	Impulse	In ms, adjustable in 1 ms	
				5	0	0 ... 500	Monitoring frequency	In 1/4 Hz, adjustable in 0.1 Hz steps ²⁾	
Function switching output Q ₁									
213 / 0xD5	Read / write	Uint	8 Bit	1	2	0, 1, 2	PNP / NPN	0 = NPN 1 = PNP 2 = auto-detect	
Control input ³⁾									
221 / 0xDD	Read / write	Uint	8 Bit	1	1	0, 1	Control input PIN 2	0 = PIN 2 disable 1 = PIN 2 active	

SYSTEM COMMANDS									
Index dec / hex	Access	Data type	Length		Function dec / hex	Range	Description	Comment	
2 / 0x02	Write	Uint	8 Bit		64 / 0x40		Teach apply	Adopt teach values on sensor	
					65 / 0x41		Single value teach - switching point 1	The switching point is on the teach value	
					66 / 0x42		Single value teach - switching point 2		
					67 / 0x43		Two value teach - teachpoint 1 for switching point 1	The switching point is in the middle of both teachpoints	
					68 / 0x44		Two value teach - teachpoint 2 for switching point 1		
					69 / 0x45		Two value teach - teachpoint 1 for switching point 2		
					70 / 0x46		Two value teach - teachpoint 2 for switching point 2		
					71 / 0x47		Dynamic teach - switching point 1 - start	The switching point is in the middle of the min. / max. value	
					72 / 0x48		Dynamic teach - switching point 1 - stop		
					73 / 0x49		Dynamic teach - switching point 2 - start		
					74 / 0x4A		Dynamic teach - switching point 2 - stop		
					79 / 0x4F		Teach cancel		
					160 / 0xA0		Emitter off		
					161 / 0xA1		Emitter on		
					162 / 0xA2		Reset switching channel	Reset of current switching channel	
	175 / 0xAF		Detect sensor	1x activated - sensor flashes 60 s 2x activated - permanent flashing 3x activated - stop permanent flashing					
	128 / 0x80		Reset sensor						
	130 / 0x82		Factory setting						

EVENTS				
Event	Status value	Warning		
20480 / 0x5000	4	Error	Device hardware fault	Default: deactivated ⁴⁾
20497 / 0x5011	4	Error	Non-volatile memory loss	
65425 / 0xFF91	0	Notice	Data storage - upload request	
16384 / 0x4000	4	Error	Temperature fault	Temperature range exceeded; default: deactivated ⁴⁾

²⁾ Differs to real frequency ± 10 %

³⁾ Only 4-pin version

⁴⁾ For activation use function 0x51